APPENDIX A

```
% BEGINNING OF PSEUDO CODE

% compute scale factor A, and time constants a, b from physical system
% parameters

A = Vmax * Kt / (Re * Rm + Kt * Kb) * l * k;

p1 = 1/Jm/Ie * (-Ie * Rm - Re * Jm + sqrt(Ie^2 * Rm^2 - 2 * Re * Rm * Ie * Jm
     + Re^2 * Jm^2 - 4 * Kt * Kb * Ie * Jm)) / 2;
p2 = 1/Jm/Ie * (-Ie * Rm - Re * Jm - sqrt(Ie^2 * Rm^2 - 2 * Re * Rm * Ie * Jm
     + Re^2 * Jm^2 - 4 * Kt * Kb * Ie * Jm)) / 2;

a = max(-p1,-p2)
b = min(-p1,-p2)

% make initial guesses for step durations

et1 = 1;
et2 = .005;
et3 = 1;

% set maximum iteration count

Nmax = 1000;

for j = 1:Nmax
% save old values of step time intervals
et3old = et3;
```

```
et2old = et2;
et1old = et1;

% iterate for switch times using fixed voltage level Vmax

et3 =   -log(1.0 / 2.0 - exp(-et1 * a) / 2 + exp(-et2 * a)) / a;
et2 =   1/b * log(2.0) + 3 * et3 - 1/b * log(2 * exp(1/A * b * X) * exp(et3
        * b) - sqrt( 4.0) * sqrt(exp(1/A * b * X)) * exp(et3 * b) *
        sqrt(exp(1/A * b * X)+exp(et3 * b)^2 - 2 * exp(et3 * b)));
et1 = - (-2 * A * et2 + 2 * A * et3 - X) / A;

if norm([et3old - et3 et2old - et2 et1old - et1], inf) <= eps * 2
        break
end
if j==Nmax
                error(['error - failure to converge after ', num2str(Nmax),'
        iterations'])
end
end

% round up pulse duration to nearest sample interval,
% convert to intervals between steps to make sure that voltage
% requirements will not increase (beyond Vmax).

dt1=ceil((et1 - et2) / dt) * dt;
dt2=ceil((et2 - et3) / dt) * dt;
dt3=ceil((et3) / dt) * dt;

et123 = [et1, et2, et3]
% convert back to total step duration.
```

et1 = dt1 + dt2 + dt3;

et2 = dt2 + dt3;

et3 = dt3;

% In the following, the original constraints equations involving XF1, XF2,
% and XF3 have been modified to include a variable voltage level applied at
% each step (instead of the fixed maximum (+/-) Vmax).

% The original equations for XF1, XF2, and XF3 follow:

% $XF_1(t_{end}) = V_0F_1(t_{tend} - t_0) - 2V_0F_1(t_{end} - t_1) + 2V_0F_1(t_{end} - t_2)$

% $XF_2(t_{end}) = V_0F_2(t_{tend} - t_0) - 2V_0F_2(t_{end} - t_1) + 2V_0F_1(t_{end} - t_2)$

% $XF_3(t_{end}) = V_0F_3(t_{tend} - t_0) - 2V_0F_2(t_{end} - t_1) + 2V_0F_1(t_{end} - t_2)$

% And the modified equation including adjustable relative levels of voltage
% L1, L2 and L3 are:

% $XF_1(t_{end}) = L_1V_0F_1(t_{tend} - t_0) - L_2V_0F_1(t_{end} - t_1) + L_3V_0F_1(t_{end} - t_2)$

% $XF_2(t_{end}) = L_1V_0F_2(t_{tend} - t_0) - L_2V_0F_2(t_{end} - t_1) + L_3V_0F_1(t_{end} - t_2)$

% $XF_3(t_{end}) = L_1V_0F_3(t_{tend} - t_0) - L_2V_0F_2(t_{end} - t_1) + L_3V_0F_1(t_{end} - t_2)$

% And the corresponding constraint equations are:

% $XF_1(t_{end})$ = Finalpos

% $XF_2(t_{end}) = 0$

% $XF_3(t_{end}) = 0$

% Where all of the times indicated have discrete values, e.g. corresponding to
% the controller update rate.

```
% It should be noted that after the digital switch times are fixed, the
constraint
% equations derived from the equations above form a linear set of
equations in
% the unknown relative voltage levels L1, L2 and L3 and any standard
linear
% method can be used to solve for the relative voltage levels.  In the
equations
% for (L1, L2 and L3) that follow, the solution was obtained by algebraic
% means (and are not particularly compact.)

% compute new relative voltage step levels
% L1, L2 and L3 are nominally assigned to "1", "-2" and "+2",
respectively
s1 =  X * (exp(-et3 * b) * exp(-et2 * a) + exp(-et3 * a) + exp(-et2 *b ) -exp(-et2
      *b) * exp(-et3 * a) - exp(-et2 * a) - exp(-et3 *b ));
s2 =  1 / (et2 * exp(-et1 * b) * exp(-et3 * a) + exp(-et2 * b) * et3 *
          exp(-et1 * a)- et2 * exp(-et3 * a) - et2 * exp(-et1 * b)  -et3 *
          exp(-et1 * a) - exp(-et2 * b) * et3+exp(-et3 * b) * et1 * exp(-et2 *
      a) + exp(-et3 * a) * et1 + exp(-et2 * b) * et1 - exp(-et2 * b) * et1 *
          exp(-et3 * a) - et3 * exp(-et1 * b) * exp(-et2 * a) - exp(-et2 * a) *
      et1 - exp(-et3 * b) * et1 - exp(-et3 * b) * et2 * exp(-et1 * a) + et3 *
          exp(-et1 * b) + et2 * exp(-et1 * a) + exp(-et3 * b) * et2 + et3 *
          exp(-et2 * a)) / A;

      L1 =   s1 * s2;

s1 =  1 / (et2 * exp(-et1 * b) * exp(-et3 * a) + exp(-et2 * b) * et3 *
          exp(-et1 * a) - et2 * exp(-et3 * a) - et2 * exp(-et1 * b) - et3 *
          exp(-et1 * a) - exp(-et2 * b) * et3 + exp(-et3 * b) * et1 *
```

```
exp(-et2 * a) + exp(-et3 * a) * et1+exp(-et2 * b) * et1 -
exp(-et2 * b) * et1 * exp(-et3 * a) - et3 * exp(-et1 * b) *
exp(-et2 * a) - exp(-et2 * a) * et1 - exp(-et3 * b) * et1 - exp(-et3 *
b) * et2 * exp(-et1 * a) + et3 * exp(-et1 * b) + et2 * exp(-et1 * a) +
exp(-et3 *b ) * et2 + et3 * exp(-et2 * a)) * X;
s2 = (exp(-et2 * b) * exp(-et1 * a) - exp(-et1 * a) - exp(-et2 * b) -
exp(-et1 * b) * exp(-et2 * a) + exp(-et1 * b) + exp(-et2 * a)) / A;
L3 = s1*s2;

s1 = exp(-et1 * a) - exp(-et3 * a) + exp(-et3 * b) - exp(-et1 * b) -
exp(-et3 * b) * exp(-et1 * a) + exp(-et1 * b) * exp(-et3 * a);
s2 = X / (et2 * exp(-et1 * b) * exp(-et3 * a) + exp(-et2 * b) * et3 *
exp(-et1 * a) - et2 * exp(-et3 * a) - et2 * exp(-et1 * b) - et3 *
exp(-et1 * a) - exp(-et2 * b) * et3 + exp(-et3 * b) * et1 * exp(-et2 *
a) + exp(-et3 * a) * et1 + exp(-et2 * b) * et1 - exp(-et2 * b) * et1 * exp(-
et3 * a) - et3 * exp(-et1 * b) * exp(-et2 *a ) - exp(-et2 * a) * et1-exp(-et3 *
b) * et1 - exp(-et3 * b) * et2 * exp(-et1 * a) + et3 *
exp(-et1 * b) + et2 * exp(-et1 * a) + exp(-et3 * b) * et2 + et3 *
exp(-et2 * a)) / A;

L2 = s1 * s2;

% convert accumulated voltage steps to sequential voltage level
V1 = Vmax * (L1);
V2 = Vmax * (L1 + L2);
V3 = Vmax * (L1 + L2 + L3);

% END OF PSEUDO CODE
```